



Wireless Presenting

Share your screen wirelessly from any device with our i3ALLSYNC HDMI Transmitter. Start sharing at the push of a button, without any installation. It is as easy as that!

All you need is the i3ALLSYNC wireless presenting app on your display, which is integrated on i3TOUCH P11, P12, E10r and i3HUDDLE. Plug the transmitter in to your laptop (or other suitable device). Press the button to share your screen. It's simple, fast and effective.

Product information

Model name	i3ALLSYNC HDMI Transmitter
Size	65 mm x 65 mm x 20 mm (HDMI cable: 150 mm and USB cable 250 mm)
Transmission quality	Real time wireless mirroring of image (1080p supported at 60hz) and sound
Compatible device	HDMI supported PC, tablet, camcorder, game console, etc Smart pad such as Galaxy Tab, iPad and smartphone supported if gender charger is connected.
OS Independent	Compatible with Windows, Mac, Android and Linux
Wi-Fi	WiFi 802.11 b/g/n 2.4G 2T2R
Power Supply	USB input 5V 1A
Splitscreen support	Available on i3HUDDLE and i3ALLSYNC TOUCH Stand-alone Receiver
Operating range	In connection range of WiFi router.
Touch back	Control your computer from the display screen without remote.
Slide Switch	

Environmental conditions

Operating Temperature	-5°C - 45°C
Operating Humidity	20% - 80% RH Non Condensation
Storage temperature	-20°C - 60°C
Storage Humidity	5% - 93% RH Non Condensation

LED

Color	Led Action	Status
Red	Lights up constantly	Standby
Red	Flash three seconds and stop three seconds	Connection failed
Red	Blink	Error
Green	Blink	Pairing
Green	Lights up constantly	Paired and Ready
Blue	Lights up constantly	Mirroring
Yellow	Lights up constantly	Without HDMI source
White	Blink	Waiting for pairing

Package content

i3ALLSYNC HDMI Transmitter	

How-to-use manual

Optional accessovries

i3ALLSYNC Transmitter storage



Works with

Video Mode

Presentation Mode







presentation.



video and audio experience.

The latency between the transmitter and

receiver means less latency and delay in

Smooth video display due to higher

frames per second. User enjoys better

The i3ALLSYNC Hardware Transmitter is OS independent.
Touchback only available on Windows and macOS (as transmitter).
Make sure that your device supports touch functionality.

CONTACT

office@hauser.lu Tél.: 48.16.60

